





# LamaPLC: D6T Omron Non-Contact Thermal Sensors with I<sup>2</sup>C communication





The Omron D6T series consists of highly sensitive MEMS thermal sensors that measure surface temperature non-contact via infrared detection. Unlike conventional motion sensors, they can detect stationary humans based on their body heat, making them suitable for energy conservation and security applications.

- **Non-Contact Measurement:** Uses thermopile elements to absorb radiant energy from objects and convert it into a temperature reading.
- **Presence Detection:** A key strength is the ability to detect both moving and stationary humans and objects, unlike typical pyroelectric sensors that rely solely on motion.
- **High Signal-to-Noise Ratio (SNR):** Omron's unique MEMS and ASIC technology delivers a high SNR, ensuring stable, accurate temperature measurements.
- **Digital Output:** Provides a direct digital temperature value via an I<sup>2</sup>C interface, simplifying software design and enhancing noise immunity.
- **Compact Size:** The sensors integrate all components (silicon lens, thermopile, ASIC) into a compact, space-saving package suitable for embedded applications.
- **Various Array Options:** Available in different configurations, including single-element (1×1), strip (1×8), and array (4×4, 32×32) formats, to suit various field-of-view (FoV) requirements.

## Operation

The sensor directs far-infrared (radiant heat) onto a thermopile, producing an electromotive force proportional to temperature. An internal ASIC then converts this into a digital temperature reading, which is sent through the I<sup>2</sup>C bus, easing software development. Unlike pyroelectric sensors that only detect motion, the D6T can detect stationary objects and humans based on their body heat.

Type of measurement	Model	Power voltage	Measurement, range, accuracy	Communication	Note
 Non-Contact Thermal Sensor	Omron <b>D6T-32L</b> 	5V	Number of elements: 1024 (32 × 32) Current consumption: 19 mA Object temperature detection: D6T-32L-01A: 0 to 200°C	I <sup>2</sup> C	Response time: 200 msec <a href="#">Arduino lib</a>
 Non-Contact Thermal Sensor	Omron <b>D6T-44L</b> 	5V	Number of elements: 16 (4 × 4) Current consumption: 5 mA Object temperature detection: D6T-44L-06: 5 .. 50°C D6T-44L-06H: 5 .. 200°C	I <sup>2</sup> C	Response time: 300 msec <a href="#">Arduino lib</a>

Type of measurement	Model	Power voltage	Measurement, range, accuracy	Communication	Note
 Non-Contact Thermal Sensor	Omron <b>D6T-8L</b> 	5V	Number of elements: 8 (1 × 8) Current consumption: 5 mA Object temperature detection: D6T-8L-09: 5 .. 50°C D6T-8L-09H: 5 .. 200°C	I <sup>2</sup> C	Response time: 250 msec <a href="#">Arduino lib</a>
 Non-Contact Thermal Sensor	Omron <b>D6T-1A</b> 	5V	Number of elements: 1 (1 × 1) Current consumption: 3.5 mA Object temperature detection: D6T-1A-01: 5 .. 50°C D6T-1A-02: -40 .. 80°C	I <sup>2</sup> C	Response time: 100 msec <a href="#">Arduino lib</a>



If you'd like to support the development of the site with the price of a coffee — or a few — [please do so here](#).

Here's a handy tip: you can quickly save this page as a PDF by clicking "export to PDF" in the menu on the right side of the screen.

2026/02/14 23:38

## Arduino & D6T-1A

To read the Omron D6T-1A (D6T-1A-01 or D6T-1A-02) with an Arduino, you use the I<sup>2</sup>C interface. The sensor has a fixed 7-bit address of **0x0A**.

### Wiring (5V Logic)

The D6T-1A requires a 4.5V to 5.5V supply.

- **VCC:** Arduino 5V
- **GND:** Arduino GND
- **SDA:** Arduino Pin A4 (on Uno)
- **SCL:** Arduino Pin A5 (on Uno)
- **Pull-up Resistors:** Many breakout boards include these, but if yours does not, use 10kΩ resistors from SDA and SCL to 5V.

### Arduino Example Code

This code uses the standard *Wire.h* library to request a 5-byte data packet (1 byte for ambient temperature PTAT, 2 bytes for the object temperature, and a PEC error check byte).

```
#include <Wire.h>

#define D6T_ADDR 0x0A // I2C 7-bit address
#define D6T_CMD 0x4C // Read command

void setup() {
  Wire.begin();
  Serial.begin(115200);
  Serial.println("Omron D6T-1A Initialized");
}

void loop() {
  uint8_t rbuf[5]; // D6T-1A returns 5 bytes (2 for PTAT, 2 for Object, 1
  for PEC)

  // Step 1: Send command to sensor
  Wire.beginTransmission(D6T_ADDR);
  Wire.write(D6T_CMD);
  Wire.endTransmission();

  // Step 2: Request 5 bytes
  Wire.requestFrom(D6T_ADDR, 5);

  int i = 0;
  while (Wire.available() && i < 5) {
    rbuf[i++] = Wire.read();
  }

  // Step 3: Convert data (Little Endian: Lower byte + Higher byte << 8)
  // Temperature = raw_value * 0.1
  float t_ptat = (rbuf[0] + (rbuf[1] << 8)) * 0.1;
  float t_obj = (rbuf[2] + (rbuf[3] << 8)) * 0.1;

  Serial.print("Ambient (PTAT): "); Serial.print(t_ptat, 1); Serial.print("
  C | ");
  Serial.print("Object: "); Serial.print(t_obj, 1); Serial.println(" C");

  delay(500);
}
```

## Key Technical Details

- **Data Format:** The sensor returns data in 0.1°C increments. For example, a value of 255 equals 25.5°C.
- **PTAT:** This refers to “Proportional To Absolute Temperature,” which is the internal ambient temperature of the sensor unit.
- **PEC (Packet Error Check):** The 5th byte is a CRC-8 checksum to ensure data integrity.
- **Stationary Detection:** Unlike PIR sensors, the D6T can detect a stationary human presence by reading radiant heat rather than motion.

## I<sup>2</sup>C topics on lamaPLC

Page	Date	Tags
• <a href="#">lamaPLC Communication: 1-Wire</a>	2026/04/23 21:51	1-wire, communication, bus, microlan, i2c, uart, usart, ds18b20
• <a href="#">lamaPLC Communication: I<sup>2</sup>C</a>	2025/09/23 21:25	i2c, i c, smbus, philips, bus, communication, arduino
• <a href="#">lamaPLC project: Senson SCD CO<sup>2</sup> measurement module</a>	2026/04/15 19:34	scd30, scd40, scd41, iaq, ndir, sensor, i2c, arduino code
• <a href="#">LamaPLC: AHT10 Modul</a>	2026/03/22 03:14	communication, i2c, temperature, humidity, sensor, aht, aht 10, modul
• <a href="#">LamaPLC: AHT20 / BMP280 Modul</a>	2026/04/23 21:52	bmp280, aht20, adafruit, temperature, humidity, pressure, sensor, arduino, code, i2c
• <a href="#">LamaPLC: APDS - Avago ALS and proximity detection sensors with I<sup>2</sup>C communication</a>	2026/04/23 21:52	avago, apds-9900, apds-9930, apds-9960, als, proximity, detection, gesture recognition, gesture, i2c, communication, sensor, arduino, code
• <a href="#">lamaPLC: Arduino Modul: BME680</a>	2026/05/12 18:40	code, c, 2026, arduino, bme680, sensor, i2c, comunication
• <a href="#">lamaPLC: AS5600 Magnetic Induction Angle Measurement Sensor Module</a>	2026/05/13 00:06	communication, i2c, as5600, as-5600, magnetic, induction, angle, sensor
• <a href="#">lamaPLC: Bi-Directional Logic Level Converter 3.3V ↔ 5V</a>	2026/04/12 00:34	bi-directional, logic level converter, i2c, uart, spi
• <a href="#">LamaPLC: BMP/BME Bosch Temperature/Humidity/Pressure sensors with I<sup>2</sup>C communication</a>	2026/04/23 21:52	bme280, bme680, bme688, bmp180, bmp280, hw-611, hw611, bosch, temperature, humidity, pressure, sensor, arduino, i2c, communication, ai, cjmcu, volatile organic compounds, vocs, volatile sulfur compounds, vscs, iaq
• <a href="#">LamaPLC: CJMCU-219/INA-219 breakout board/IC with I<sup>2</sup>C communication</a>	2026/04/23 21:52	cjmcu-219, ina-219, ina219, breakout board, i2c, communication, sensor, voltage, current, arduino, code, cjmcu
• <a href="#">LamaPLC: CJMCU-3216 / AP-3216 integrated digital ambient light and proximity sensor module/IC with I<sup>2</sup>C communication</a>	2026/04/23 21:52	cjmcu-3216, cjmcu, ap-3216, ap3216, ambient light, proximity, sensor, arduino, code, i2c, communication
• <a href="#">lamaPLC: CJMCU-811 CCS811 Gas Sensor (VOCs TVOC CO<sub>2</sub>)</a>	2026/04/23 21:52	cjmcu-811, ccs811, gas, sensor, vocs, tvoc, eco2, co2, arduino, air quality metal oxide, mox, i2c, micropython, rp2040-eth
• <a href="#">LamaPLC: D6T Omron Non-Contact Thermal Sensors with I<sup>2</sup>C communication</a>	2026/04/23 21:52	d6t, d6t-32l, d6t-44l, d6t-8l, d6t-1a, omron, non-contact, thermal, sensor, i2c, arduino, code
• <a href="#">LamaPLC: DPS Infineon Temperature/Pressure sensors with I<sup>2</sup>C communication</a>	2026/04/23 21:52	dps310, infineon, temperature, pressure, sensor, arduino, i2c, communication, code
• <a href="#">lamaPLC: Energy, power, current, and voltage</a>	2025/05/31 23:32	i2c, i c, communication, arduino, energy, power, current, sensor, ina226

- [LamaPLC: ENS ScioSense Multi-gas sensors with I<sup>2</sup>C communication](#) 2026/04/23 21:52

[ens160](#), [sciosense](#), [gas-quality](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#), [eco2](#), [tvoc](#), [aqi](#), [indoor air quality](#), [iaq](#), [co2](#), [voc](#)
- [lamaPLC: ESP32 / ESP8266](#) 2025/11/22 00:07

[esp8266](#), [esp32](#), [esp32-c2](#), [esp32-c3](#), [esp32-c5](#), [esp32-c6](#), [esp32-c61](#), [esp32-h2](#), [esp32-s2](#), [esp32-s3](#), [esp32-p4](#), [espressif systems](#), [communication](#), [ethernet](#), [ip](#), [wi-fi](#), [thread](#), [zigbee](#), [matter](#), [homekit](#), [bluetooth](#), [mqtt](#), [adc](#), [spi](#), [uart](#), [i2c](#), [i2s](#), [rmt](#), [pwm](#), [usb](#), [usb otg](#), [twai](#)

[gas](#), [sensor](#), [i2c](#), [onewire](#), [communication](#), [mq-3](#), [mq-4](#), [mq-5](#), [mq-6](#), [mq-7](#), [mq-8](#), [mq-9](#), [mq-135](#), [gm-102b](#), [gm-302b](#), [gm-502b](#), [gm-702b](#), [alcohol](#), [ch4](#), [natural gas](#), [smoke](#), [lng](#), [co](#), [co2](#), [lpg](#), [h2](#), [iso-butane](#), [nox](#), [nh3](#), [benzene](#), [town gas](#), [formaldehyde](#), [propane](#), [humidity](#), [temperature](#), [voc](#), [grv gas sens v2](#)
- [LamaPLC: Gas sensors](#) 2023/07/01 17:29

[stmicroelectronics](#), [lsm303dlhc](#), [i2c](#), [lsm303](#), [sensor](#), [gy-511](#), [6dof](#), [pololu](#), [module](#), [arduino](#)
- [lamaPLC: GY-511 6DOF sensor module](#) 2026/04/23 21:52

[ak8963](#), [gy-9250](#), [mpu-9250](#), [9-axis](#), [motion detection](#), [magnetometer](#), [communication](#), [i c](#), [i2c](#), [spi](#)
- [LamaPLC: GY-9250 MPU-9250/6500 9-axis Attitude Sensor Board](#) 2026/04/23 21:52

[sht21](#), [htu21](#), [si7021](#), [gy-21](#), [gy-213v](#), [hdc1080](#), [gy-213v-hdc1080](#), [cjmcu](#), [cjmcu-1080](#), [texas instruments](#), [temperature](#), [humidity](#), [sensor](#), [i2c](#), [communication](#), [arduino](#), [code](#)
- [LamaPLC: HDC Texas Instruments Temperature/humidity sensors with I<sup>2</sup>C communication](#) 2026/04/23 21:52

[i2c](#), [7-segment display](#), [display](#), [ht16k33](#), [arduino](#)
- [lamaPLC: HT16K33 display controller](#) 2026/04/23 21:51

[htu](#), [htu31d](#), [htu21d](#), [htu20d](#), [sht20](#), [htu20](#), [sht21](#), [htu21](#), [si7021](#), [gy-21](#), [gy-213v](#), [hdc1080](#), [si702](#), [gy-20](#), [sht31](#), [htu31](#), [si7031](#), [gy-31](#), [te connectivity](#), [temperature](#), [humidity](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#)
- [LamaPLC: HTU TE Connectivity temperature/humidity sensors with I<sup>2</sup>C communication](#) 2026/04/23 21:52

[i2c](#), [i c](#), [communication](#), [arduino](#), [energy](#), [power](#), [current](#), [monitor](#), [sensor](#), [ina219](#), [gy-219](#), [ina226](#), [gy-216](#), [ina228](#), [gy-228](#), [ina237](#), [ina238](#), [ina260](#), [ina3221](#), [ina](#)
- [lamaPLC: INA modules with Arduino libraries](#) 2026/04/23 21:52

[i2c](#), [i c](#), [communication](#), [arduino](#), [energy](#), [power](#), [current](#), [monitor](#), [sensor](#), [ina226](#), [ina219](#), [ina](#)
- [lamaPLC: INA226 - current/voltage/power monitor with I<sup>2</sup>C communication](#) 2026/04/23 21:52

[communication](#), [i2c](#), [display](#), [lcd](#), [1602](#), [2004](#), [hd44780](#), [pcf8574](#), [pcf8574t](#), [pcf8574at](#), [arduino](#)
- [lamaPLC: LCD 1602/2004 with I<sup>2</sup>C communication](#) 2026/02/14 18:27

- [LamaPLC: MAX30100/MAX30102 Heart Rate Click Sensor Module](#) 2026/04/23 21:52 [max30102](#), [max30100](#), [heart rate click](#), [sensor](#), [communication](#), [i2c](#), [arduino](#), [code](#)
- [lamaPLC: MCP23017 / MCP23S17 16-Bit I/O Expander with Serial Interface I<sup>2</sup>C / SPI](#) 2026/04/23 21:52 [communication](#), [i2c](#), [mcp23017](#), [mcp23s17](#), [spi](#), [i o expander](#), [serial](#), [cjmcu-2317](#), [cjmcu](#)
- [lamaPLC: MLX90614 \(GY-906\) infrared non-contact thermometer](#) 2026/05/08 00:03 [communication](#), [i2c](#), [temperature](#), [mlx90614](#), [gy-906](#), [modul](#), [infrared](#), [non-contact thermometer](#), [dsp](#), [pwm](#), [smbus](#), [hailege](#)
- [lamaPLC: PCF857x I/O Expander chip/modul with I<sup>2</sup>C communication](#) 2026/05/15 01:03 [communication](#), [i2c](#), [pcf857x](#), [pcf8574](#), [pcf8574a](#), [pcf8575](#), [i o expander](#), [i o extension](#), [nxp](#), [texas instruments](#)
- [LamaPLC: Pixart PAJ7620U2 Gesture recognition sensors/module with I<sup>2</sup>C communication](#) 2026/04/23 21:52 [paj7620u2](#), [gy-paj7620](#), [pixart](#), [gesture recognition](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#)
- [lamaPLC: RP2040\\_ETH\\_Modul: I<sup>2</sup>C scanner](#) 2026/05/12 16:20 [code](#), [micropython](#), [2026](#), [rp2040 eth](#), [i2c](#), [comunication](#)
- [lamaPLC: RP2040\\_ETH\\_Modul: MLX90614 simple](#) 2026/05/12 17:06 [code](#), [micropython](#), [2026](#), [rp2040 eth](#), [i2c](#), [communication](#), [mlx90614](#)
- [lamaPLC: RP2040\\_ETH\\_Modul: Read BME 680/688 sensor data](#) 2026/05/12 21:06 [code](#), [micropython](#), [2026](#), [rp2040 eth](#), [bme680](#), [i2c](#), [sensor](#), [communication](#)
- [lamaPLC: RP2040\\_ETH\\_Modul: Read BME 680/688 sensor data and store in Modbus input registers](#) 2026/05/12 21:04 [code](#), [micropython](#), [2026](#), [rp2040 eth](#), [bme680](#), [i2c](#), [sensor](#), [communication](#)
- [LamaPLC: SC16IS750 / SC16IS752: One or two serial \(UART\) ports from microcontroller via I<sup>2</sup>C or SPI communication](#) 2026/04/23 21:52 [cjmcu-750](#), [cjmcu-752](#), [cjmcu](#), [nxp](#), [sc16is750](#), [sc16is752](#), [uart](#), [serial](#), [i2c](#), [spi](#), [modul](#), [converter](#), [arduino](#), [code](#)
- [LamaPLC: SGP Sensirion TVOC/VOC sensors with I<sup>2</sup>C communication](#) 2026/04/15 19:41 [sgp30](#), [sgp40](#), [sgp41](#), [sensirion](#), [gas-sensor](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#), [eco2](#), [voc](#), [tvoc](#), [indoor air quality](#), [iaq](#), [nox](#), [hydrogen](#)
- [LamaPLC: SHT Sensirion Temperature/humidity sensor with I<sup>2</sup>C communication](#) 2026/04/23 21:52 [sht20](#), [sht21](#), [sht25](#), [sht30](#), [sht31](#), [sht35](#), [sht40](#), [gy21](#), [temperature](#), [humidity](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#)
- [lamaPLC: Signal level converters](#) 2026/02/14 23:47 [pca9306](#), [i2c](#), [voltage](#), [level](#), [converter](#)
- [lamaPLC: st756x display drivers](#) 2026/05/20 16:17 [display](#), [driver](#), [i2c](#), [spi](#), [lcd](#), [cog](#), [oled](#), [st7565](#), [st7567](#), [gm12864](#), [gm12864-59n](#), [gm12864-03a](#), [gm12864-01a](#), [gme12864-41](#)
- [lamaPLC: TCA9548A \(HW617\); Low-Voltage 8-Channel I<sup>2</sup>C Switch Module](#) 2026/02/14 23:51 [tca9548a](#), [hw617](#), [i2c](#), [switch](#), [communication](#), [expansion board](#), [arduino](#)
- [lamaPLC: TM1637 7-segment display](#) 2026/02/14 18:26 [i2c](#), [7-segment display](#), [display](#), [tm1637](#), [arduino](#)
- [LamaPLC: TOFnnnC STMicroelectronics Time-of-Flight \(ToF\) sensors with I<sup>2</sup>C communication](#) 2026/04/23 21:52 [tof050c](#), [vl6180](#), [tof200c](#), [vl5310x](#), [tof400c](#), [vl5311x](#), [stmicroelectronics](#), [time-of-flight](#), [tof](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#)

- [LamaPLC: VL53Lnn STMicroelectronics time-of-flight \(ToF\) laser-ranging sensors with I<sup>2</sup>C communication](#)
2026/04/23 21:52
vl53l0x, vl53l1x, vl53l0 1xv2, gy-530, time-of-flight, tof, laser-ranging, i2c, communication, sensor, arduino, code
- [LamaPLC: VL6180X STMicroelectronics Time-of-Flight \(ToF\) sensor with I<sup>2</sup>C communication](#)
2026/04/23 21:52
vl6180x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code
- [lamaPLC: XGZP68xx: Silicon Pressure Sensors/Module](#)
2026/05/15 15:17
communication, i2c, sensor, modul, pressure, cfsensor, xgzp68xx, xgzp6810d, xgzp6857d, xgzp6859d, xgzp6887d, xgzp6897d, xgzp6899a, piezoresistive, capacitive
- [Magnetic angle sensors](#)
2026/04/23 21:52
magnetic angle sensor, magnetic flux, sensor, spi, i2c, pwm, communication, modul, as5047p, as5600, mt6701, mt6816, mt6835, tle5012b, amr, gmr, tmr, anisotropic magnetoresistive
- [SSH1106/SSD1306 OLED Display with I<sup>2</sup>C communication](#)
2026/02/14 18:27
i2c, oled, display, ssd1306, sh1106, ssh1106, arduino, cmos

[D6T](#), [D6T-32L](#), [D6T-44L](#), [D6T-8L](#), [D6T-1A](#), [Omron](#), [Non-Contact](#), [Thermal](#), [sensor](#), [I2C](#), [arduino](#), [code](#)

This page has been accessed for: Today: 1, Until now: 424

From: <https://lamaplc.com/> - **lamaPLC**

Permanent link: <https://lamaplc.com/doku.php?id=sensor:d6t>

Last update: **2026/04/21 20:47**

