


LamaPLC: AHT10 Modul

The AHT10 is an affordable, high-precision digital sensor module that measures both temperature and humidity. It uses a standard I²C interface for communication and is commonly used with microcontrollers such as Arduino and ESP32.



Key Specifications

- **Operating Voltage:** 1.8V to **6.0V**.
- **Temperature Range:** -40°C to +85°C with $\pm 0.3^\circ\text{C}$ typical accuracy.
- **Humidity Range:** 0% to 100% RH with $\pm 2\%$ typical accuracy.
- **Resolution:** 0.01°C for temperature and 0.024% for humidity.
- **Communication:** I²C (Default Address: 0x38).

Notable Features

- **Fully Calibrated:** It provides a calibrated digital signal directly, eliminating the need for complex external calibration.
- **Internal Components:** Equipped with a dedicated ASIC-specific chip and an improved MEMS semiconductor capacitive humidity sensor.
- **Energy Efficiency:** Extremely low power consumption (under 100 nA in sleep mode), making it ideal for battery-powered IoT devices.

Pinout Configuration

Pin	Name	Function	Typical Connection
1	VIN / VCC	Power Supply (1.8V to 6.0V)	3.3V or 5V pin
2	GND	Ground	GND pin
3	SCL	I ² C Serial Clock	SCL / A5 (Arduino Uno)
4	SDA	I ² C Serial Data	SDA / A4 (Arduino Uno)

Wiring & Integration Details

- **Voltage Levels:** While the raw AHT10 chip operates at 1.8V–3.6V, most modules include an onboard voltage regulator (like the XC6206) and level shifters, making them safe for use with 5V systems like the Arduino Uno.
- **Pull-up Resistors:** Stable I²C communication requires pull-up resistors (typically 4.7k Ω or 10k Ω) on the SDA and SCL lines. Most pre-assembled modules already have these built-in.
- **I²C Address:** The default hardware address is 0x38.

Arduino example code

To use the AHT10 sensor with an Arduino, the most common and reliable method is using the **Adafruit AHTX0** library.

This script initializes the sensor and prints temperature and humidity data to the Serial Monitor every 2 seconds.

```
#include <Wire.h>
#include <Adafruit_AHTX0.h>

Adafruit_AHTX0 aht;

void setup() {
  Serial.begin(115200);
  Serial.println("AHT10 Sensor Test");

  // Initialize I2C and the sensor
  if (!aht.begin()) {
    Serial.println("Could not find AHT10. Check wiring!");
    while (1) delay(10);
  }
  Serial.println("AHT10 found and initialized.");
}

void loop() {
  sensors_event_t humidity, temp;

  // Get new sensor events with the latest data
  aht.getEvent(&humidity, &temp);

  // Print results to Serial Monitor
  Serial.print("Temperature: ");
  Serial.print(temp.temperature);
  Serial.println(" °C");

  Serial.print("Humidity: ");
  Serial.print(humidity.relative_humidity);
  Serial.println(" % rH");

  delay(2000); // Wait 2 seconds between readings
}
```

Implementation Notes

- **Baud Rate:** Ensure your Serial Monitor is set to 115200 to match the `Serial.begin(115200)` command.
- **Polling Frequency:** While this code polls every 2 seconds, the manufacturer recommends a polling frequency of 8 to 30 seconds for long-term stability and to avoid sensor self-heating.
- **Wiring:** Connect SDA to A4 and SCL to A5 on an Arduino Uno (or the dedicated SDA/SCL pins on other boards).

I²C topics on lamaPLC

Page	Date	Tags
• lamaPLC Communication: 1-Wire	2025/05/31 21:56	1-wire , communication , bus , microlan , i2c , uart , usart , ds18b20

• lamaPLC Communication: I²C	2025/09/23 19:25	i2c, i c, smbus, philips, bus, communication, arduino
• LamaPLC: AHT10 Modul	2026/03/21 19:20	communication, i2c, temperature, humidity, sensor, aht, aht 10, modul
• LamaPLC: AHT20 / BMP280 Modul	2026/02/15 20:33	bmp280, aht20, adafruit, temperature, humidity, pressure, sensor, arduino, code, i2c
• LamaPLC: APDS - Avago ALS and proximity detection sensors with I²C communication	2026/02/14 22:24	avago, apds-9900, apds-9930, apds-9960, als, proximity, detection, gesture recognition, gesture, i2c, communication, sensor, arduino, code
• lamaPLC: AS5600 Magnetic Induction Angle Measurement Sensor Module	2026/03/28 22:07	communication, i2c, as5600, as-5600, magnetic, induction, angle, sensor
• LamaPLC: BMP/BME Bosch Temperature/Humidity/Pressure sensors with I²C communication	2026/02/15 20:40	bme280, bme680, bmp180, bmp280, hw-611, hw611, bosch, temperature, humidity, pressure, sensor, arduino, i2c, communication, cjmcu
• LamaPLC: CJMCU-219/INA-219 breakout board/IC with I²C communication	2026/02/14 23:37	cjmcu-219, ina-219, ina219, breakout board, i2c, communication, sensor, voltage, current, arduino, code, cjmcu
• LamaPLC: CJMCU-3216 / AP-3216 integrated digital ambient light and proximity sensor module/IC with I²C communication	2026/02/14 22:40	cjmcu-3216, cjmcu, ap-3216, ap3216, ambient light, proximity, sensor, arduino, code, i2c, communication
• lamaPLC: CJMCU-811 CCS811 Gas Sensor (VOCs TVOC CO₂)	2026/03/21 22:25	cjmcu-811, ccs811, gas, sensor, vocs, tvoc, eco2, co2, arduino, air quality metal oxide, mox, i2c
• LamaPLC: D6T Omron Non-Contact Thermal Sensors with I²C communication	2026/02/14 18:19	d6t, d6t-32l, d6t-44l, d6t-8l, d6t-1a, omron, non-contact, thermal, sensor, i2c, arduino, code
• LamaPLC: DPS Infineon Temperature/Pressure sensors with I²C communication	2026/02/14 18:11	dps310, infineon, temperature, pressure, sensor, arduino, i2c, communication, code
• lamaPLC: Energy, power, current, and voltage	2025/05/31 21:32	i2c, i c, communication, arduino, energy, power, current, sensor, ina226
• LamaPLC: ENS ScioSense Multi-gas sensors with I²C communication	2026/02/14 19:29	ens160, sciosense, gas-quality, i2c, communication, sensor, arduino, code, eco₂, tvoc, aqi, indoor air quality, iaq, co₂, voc
• lamaPLC: ESP32 / ESP8266	2025/11/21 23:07	esp8266, esp32, esp32-c2, esp32-c3, esp32-c5, esp32-c6, esp32-c61, esp32-h2, esp32-s2, esp32-s3, esp32-p4, espressif systems, communication, ethernet, ip, wi-fi, thread, zigbee, matter, homekit, bluetooth, mqtt, adc, spi, uart, i2c, i2s, rmt, pwm, usb, usb otg, twai

• LamaPLC: Gas sensors	2023/07/01 15:29	gas, sensor, i2c, onewire, communication, mq-3, mq-4, mq-5, mq-6, mq-7, mq-8, mq-9, mq-135, gm-102b, gm-302b, gm-502b, gm-702b, alcohol, ch4, natural gas, smoke, lng, co, co2, lpg, h2, iso-butane, nox, nh3, benzene, town gas, formaldehyde, propane, humidity, temperature, voc, grv gas sens v2
• lamaPLC: GY-511 6DOF sensor module	2026/03/22 00:26	stmicroelectronics, lsm303dlhc, i2c, lsm303, sensor, gy-511, 6dof, pololu, module, arduino
• LamaPLC: GY-9250 MPU-9250/6500 9-axis Attitude Sensor Board	2026/02/14 22:45	ak8963, gy-9250, mpu-9250, 9-axis, motion detection, magnetometer, communication, i c, i2c, spi
• LamaPLC: HDC Texas Instruments Temperature/humidity sensors with I ² C communication	2026/02/14 22:09	sht21, htu21, si7021, gy-21, gy-213v, hdc1080, gy-213v-hdc1080, cjmcu, cjmcu-1080, texas instruments, temperature, humidity, sensor, i2c, communication, arduino, code
• lamaPLC: HT16K33 display controller	2026/02/14 17:26	i2c, 7-segment display, display, ht16k33, arduino
• LamaPLC: HTU TE Connectivity temperature/humidity sensors with I ² C communication	2026/02/14 21:54	htu, htu31d, htu21d, htu20d, sht20, htu20, sht21, htu21, si7021, gy-21, gy-213v, hdc1080, si702, gy-20, sht31, htu31, si7031, gy-31, te connectivity, temperature, humidity, i2c, communication, sensor, arduino, code
• lamaPLC: INA modules with Arduino libraries	2026/03/28 18:02	i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina219, ina226, ina228, ina237, ina238, ina260, ina3221, ina
• lamaPLC: INA226 - current/voltage/power monitor with I ² C communication	2026/02/14 23:58	i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina226, ina219, ina
• lamaPLC: LCD 1602/2004 with I ² C communication	2026/02/14 17:27	communication, i2c, display, lcd, 1602, 2004, hd44780, pcf8574, pcf8574t, pcf8574at, arduino
• LamaPLC: MAX30100/MAX30102 Heart Rate Click Sensor Module	2026/02/14 23:38	max30102, max30100, heart rate click, sensor, communication, i2c, arduino, code
• lamaPLC: MCP23017 / MCP23S17 16-Bit I/O Expander with Serial Interface I ² C / SPI	2026/02/14 22:52	communication, i2c, mcp23017, mcp23s17, spi, i o expander, serial, cjmcu-2317, cjmcu
• LamaPLC: Pixart PAJ7620U2 Gesture recognition sensors/module with I ² C communication	2026/02/14 22:23	paj7620u2, gy-paj7620, pixart, gesture recognition, i2c, communication, sensor, arduino, code
• LamaPLC: SC16IS750 / SC16IS752: One or two serial (UART) ports from microcontroller via I ² C or SPI communication	2026/02/14 22:53	cjmcu-750, cjmcu-752, cjmcu, nxp, sc16is750, sc16is752, uart, serial, i2c, spi, modul, converter, arduino, code

- [LamaPLC: SGP Sensirion Gas-sensors with I²C communication](#) 2026/02/15 20:27 [sgp30, sgp40, sgp41, sensirion, gas-sensor, i2c, communication, sensor, arduino, code, eco2, voc, tvoc, indoor air quality, iaq, nox, hydrogen](#)
- [LamaPLC: SHT Sensirion Temperature/humidity sensor with I²C communication](#) 2026/02/15 20:29 [sht20, sht21, sht25, sht30, sht31, sht35, sht40, gy21, temperature, humidity, i2c, communication, sensor, arduino, code](#)
- [lamaPLC: Signal level converters](#) 2026/02/14 22:47 [pca9306, i2c, voltage, level, converter](#)
- [lamaPLC: TCA9548A \(HW617\); Low-Voltage 8-Channel I²C Switch Module](#) 2026/02/14 22:51 [tca9548a, hw617, i2c, switch, communication, expansion board, arduino](#)
- [lamaPLC: TM1637 7-segment display](#) 2026/02/14 17:26 [i2c, 7-segment display, display, tm1637, arduino](#)
- [LamaPLC: TOFnnnC STMicroelectronics Time-of-Flight \(ToF\) sensors with I²C communication](#) 2026/02/14 22:22 [tof050c, vl6180, tof200c, vl53l0x, tof400c, vl53l1x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code](#)
- [LamaPLC: VL53Lnn STMicroelectronics time-of-flight \(ToF\) laser-ranging sensors with I²C communication](#) 2026/02/14 22:21 [vl53l0x, vl53l1x, vl53l0 1xv2, gy-530, time-of-flight, tof, laser-ranging, i2c, communication, sensor, arduino, code](#)
- [LamaPLC: VL6180X STMicroelectronics Time-of-Flight \(ToF\) sensor with I²C communication](#) 2026/02/14 22:22 [vl6180x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code](#)
- [Magnetic angle sensors](#) 2026/03/05 20:19 [magnetic angle sensor, magnetic flux, sensor, spi, i2c, pwm, communication, modul, as5047p, as5600, mt6701, mt6816, mt6835, tle5012b, amr, gmr, tmr, anisotropic magnetoresistive](#)
- [SSH1106/SSD1306 OLED Display with I²C communication](#) 2026/02/14 17:27 [i2c, oled, display, ssd1306, sh1106, ssh1106, arduino, cmos](#)

[communication, i2c, temperature, humidity, sensor, aht, AHT 10, modul](#)

This page has been accessed for: Today: 1, Until now: 53

From: <http://lamaplc.com/> - **lamaPLC**

Permanent link: <http://lamaplc.com/doku.php?id=sensor:aht10&rev=1774121542>

Last update: **2026/03/21 19:32**

