

LamaPLC: APDS - Avago ALS and proximity detection sensors with I²C communication

The Avago APDS-9900, APDS-9930, and APDS-9960 are a series of integrated optical sensor modules that primarily offer ambient light sensing (ALS) and proximity detection, with the APDS-9960 adding advanced gesture recognition and RGB color sensing.



Feature Comparison

Feature	Avago APDS-9900	Avago APDS-9930	Avago APDS-9960
Type	Approximates Human Eye Response	Approximates Human Eye Response	Ambient Light and RGB Color Sensing, Proximity Sensing, and Gesture Detection in an Optical Module
Ambient Light Sensing (ALS)	Yes (Clear & IR channels)	Yes (Clear & IR channels)	Yes (RGBC - Red, Green, Blue, Clear)
Proximity Detection	Yes	Yes (calibrated to 100mm)	Yes (calibrated to 100mm)
Gesture Detection	No	No	Yes (Up, Down, Left, Right, etc.)
RGB Color Sensing	No	No	Yes
Interface	I ² C	I ² C	I ² C
Operating Voltage	2.5V - 3.6V	2.2V - 3.6V	2.4V - 3.6V
Key Application	Simple light/proximity in phones	Power-saving display management	HMI, robotics, complex touchless control

Communication: I²C communication, default address: 0x39



If you'd like to support the development of the site with the price of a coffee — or a few — [please do so here](#).

Here's a handy tip: you can quickly save this page as a PDF by clicking "export to PDF" in the menu on the right side of the screen.

2026/02/14 23:38

Arduino wiring

Pin	Name	Function
VL	LED Power	Optional power for the IR LED (if not jumpered to VCC). Usually 3.0V - 4.5V
VCC	Power	2.4V to 3.6V. (Note: Use 3.3V for Arduino; 5V will damage the chip without a regulator)
GND	Ground	0V Reference

Pin	Name	Function
SCL	I ² C Clock	Serial clock line for I ² C communication
SDA	I ² C Data	Serial data line for I ² C communication
INT	Interrupt	Active Low. Goes LOW when a gesture or proximity event is triggered. For gesture sensing, it is highly recommended to connect the INT pin to a hardware interrupt pin (e.g., Digital Pin 2 on Arduino) to ensure the sensor's FIFO buffer is read immediately when data is ready.

Arduino code

FOR APDS-9960 running on an Arduino, the SparkFun APDS-9960 Library "SparkFun APDS9960" is the industry standard.

```
#include <Wire.h>
#include <SparkFun_APDS9960.h>

#define APDS9960_INT 2 // Must be an interrupt pin
SparkFun_APDS9960 apds = SparkFun_APDS9960();
volatile bool isr_flag = false;

void setup() {
  Serial.begin(9600);
  pinMode(APDS9960_INT, INPUT);

  // Initialize interrupt service routine
  attachInterrupt(digitalPinToInterrupt(APDS9960_INT), interruptRoutine,
  FALLING);

  if (apds.init()) {
    Serial.println(F("APDS-9960 initialization complete"));
  } else {
    Serial.println(F("Something went wrong during APDS-9960 init!"));
  }

  // Start sensor gesture engine
  if (apds.enableGestureSensor(true)) {
    Serial.println(F("Gesture sensor is now running"));
  } else {
    Serial.println(F("Something went wrong during gesture sensor init!"));
  }
}

void loop() {
  if (isr_flag) {
    detachInterrupt(digitalPinToInterrupt(APDS9960_INT));
    handleGesture();
    isr_flag = false;
    attachInterrupt(digitalPinToInterrupt(APDS9960_INT), interruptRoutine,
  FALLING);
  }
}
```

```

}

void interruptRoutine() {
  isr_flag = true;
}

void handleGesture() {
  if (apds.isGestureAvailable()) {
    switch (apds.readGesture()) {
      case DIR_UP:      Serial.println("UP");      break;
      case DIR_DOWN:    Serial.println("DOWN");    break;
      case DIR_LEFT:    Serial.println("LEFT");    break;
      case DIR_RIGHT:   Serial.println("RIGHT");   break;
      case DIR_NEAR:    Serial.println("NEAR");    break;
      case DIR_FAR:     Serial.println("FAR");     break;
      default:          Serial.println("NONE");
    }
  }
}
}
}

```

I²C topics on lamaPLC

Page	Date	Tags
• lamaPLC Communication: 1-Wire	2026/04/23 21:51	1-wire , communication , bus , microlan , i2c , uart , usart , ds18b20
• lamaPLC Communication: I²C	2025/09/23 21:25	i2c , i c , smbus , philips , bus , communication , arduino
• lamaPLC project: Senson SCD CO² measurement module	2026/04/15 19:34	scd30 , scd40 , scd41 , iaq , ndir , sensor , i2c , arduino code
• LamaPLC: AHT10 Modul	2026/03/22 03:14	communication , i2c , temperature , humidity , sensor , aht , aht 10 , modul
• LamaPLC: AHT20 / BMP280 Modul	2026/04/23 21:52	bmp280 , aht20 , adafruit , temperature , humidity , pressure , sensor , arduino , code , i2c
• LamaPLC: APDS - Avago ALS and proximity detection sensors with I²C communication	2026/04/23 21:52	avago , apds-9900 , apds-9930 , apds-9960 , als , proximity , detection , gesture recognition , gesture , i2c , communication , sensor , arduino , code
• lamaPLC: Arduino Modul: BME680	2026/05/12 18:40	code , c , 2026 , arduino , bme680 , sensor , i2c , comunication
• lamaPLC: AS5600 Magnetic Induction Angle Measurement Sensor Module	2026/05/13 00:06	communication , i2c , as5600 , as-5600 , magnetic , induction , angle , sensor
• lamaPLC: Bi-Directional Logic Level Converter 3.3V ↔ 5V	2026/04/12 00:34	bi-directional , logic level converter , i2c , uart , spi

<ul style="list-style-type: none"> • LamaPLC: BMP/BME Bosch Temperature/Humidity/Pressure sensors with I²C communication 	2026/04/23 21:52	bme280, bme680, bme688, bmp180, bmp280, hw-611, hw611, bosch, temperature, humidity, pressure, sensor, arduino, i2c, communication, ai, cjmcu, volatile organic compounds, vocs, volatile sulfur compounds, vscs, iaq
<ul style="list-style-type: none"> • LamaPLC: CJMCU-219/INA-219 breakout board/IC with I²C communication 	2026/04/23 21:52	cjmcu-219, ina-219, ina219, breakout board, i2c, communication, sensor, voltage, current, arduino, code, cjmcu
<ul style="list-style-type: none"> • LamaPLC: CJMCU-3216 / AP-3216 integrated digital ambient light and proximity sensor module/IC with I²C communication 	2026/04/23 21:52	cjmcu-3216, cjmcu, ap-3216, ap3216, ambient light, proximity, sensor, arduino, code, i2c, communication
<ul style="list-style-type: none"> • lamaPLC: CJMCU-811 CCS811 Gas Sensor (VOCs TVOC CO2) 	2026/04/23 21:52	cjmcu-811, ccs811, gas, sensor, vocs, tvoc, eco2, co2, arduino, air quality metal oxide, mox, i2c, micropython, rp2040-eth
<ul style="list-style-type: none"> • LamaPLC: D6T Omron Non-Contact Thermal Sensors with I²C communication 	2026/04/23 21:52	d6t, d6t-32l, d6t-44l, d6t-8l, d6t-1a, omron, non-contact, thermal, sensor, i2c, arduino, code
<ul style="list-style-type: none"> • LamaPLC: DPS Infineon Temperature/Pressure sensors with I2C communication 	2026/04/23 21:52	dps310, infineon, temperature, pressure, sensor, arduino, i2c, communication, code
<ul style="list-style-type: none"> • lamaPLC: Energy, power, current, and voltage 	2025/05/31 23:32	i2c, i c, communication, arduino, energy, power, current, sensor, ina226
<ul style="list-style-type: none"> • LamaPLC: ENS ScioSense Multi-gas sensors with I²C communication 	2026/04/23 21:52	ens160, sciosense, gas-quality, i2c, communication, sensor, arduino, code, eco2, tvoc, aqi, indoor air quality, iaq, co2, voc
<ul style="list-style-type: none"> • lamaPLC: ESP32 / ESP8266 	2025/11/22 00:07	esp8266, esp32, esp32-c2, esp32-c3, esp32-c5, esp32-c6, esp32-c61, esp32-h2, esp32-s2, esp32-s3, esp32-p4, espressif systems, communication, ethernet, ip, wi-fi, thread, zigbee, matter, homekit, bluetooth, mqtt, adc, spi, uart, i2c, i2s, rmt, pwm, usb, usb otg, twai
<ul style="list-style-type: none"> • LamaPLC: Gas sensors 	2023/07/01 17:29	gas, sensor, i2c, onewire, communication, mq-3, mq-4, mq-5, mq-6, mq-7, mq-8, mq-9, mq-135, gm-102b, gm-302b, gm-502b, gm-702b, alcohol, ch4, natural gas, smoke, lng, co, co2, lpg, h2, iso-butane, nox, nh3, benzene, town gas, formaldehyde, propane, humidity, temperature, voc, grv gas sens v2
<ul style="list-style-type: none"> • lamaPLC: GY-511 6DOF sensor module 	2026/04/23 21:52	stmicroelectronics, lsm303dlhc, i2c, lsm303, sensor, gy-511, 6dof, pololu, module, arduino
<ul style="list-style-type: none"> • LamaPLC: GY-9250 MPU-9250/6500 9-axis Attitude Sensor Board 	2026/04/23 21:52	ak8963, gy-9250, mpu-9250, 9-axis, motion detection, magnetometer, communication, i c, i2c, spi

• LamaPLC: HDC Texas Instruments Temperature/humidity sensors with I ² C communication	2026/04/23 21:52	sht21, htu21, si7021, gy-21, gy-213v, hdc1080, gy-213v-hdc1080, cjmcu, cjmcu-1080, texas instruments, temperature, humidity, sensor, i2c, communication, arduino, code
• lamaPLC: HT16K33 display controller	2026/04/23 21:51	i2c, 7-segment display, display, ht16k33, arduino
• LamaPLC: HTU TE Connectivity temperature/humidity sensors with I ² C communication	2026/04/23 21:52	htu, htu31d, htu21d, htu20d, sht20, htu20, sht21, htu21, si7021, gy-21, gy-213v, hdc1080, si702, gy-20, sht31, htu31, si7031, gy-31, te connectivity, temperature, humidity, i2c, communication, sensor, arduino, code
• lamaPLC: INA modules with Arduino libraries	2026/04/23 21:52	i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina219, gy-219, ina226, gy-216, ina228, gy-228, ina237, ina238, ina260, ina3221, ina
• lamaPLC: INA226 - current/voltage/power monitor with I ² C communication	2026/04/23 21:52	i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina226, ina219, ina
• lamaPLC: LCD 1602/2004 with I ² C communication	2026/02/14 18:27	communication, i2c, display, lcd, 1602, 2004, hd44780, pcf8574, pcf8574t, pcf8574at, arduino
• LamaPLC: MAX30100/MAX30102 Heart Rate Click Sensor Module	2026/04/23 21:52	max30102, max30100, heart rate click, sensor, communication, i2c, arduino, code
• lamaPLC: MCP23017 / MCP23S17 16-Bit I/O Expander with Serial Interface I ² C / SPI	2026/04/23 21:52	communication, i2c, mcp23017, mcp23s17, spi, i o expander, serial, cjmcu-2317, cjmcu
• lamaPLC: MLX90614 (GY-906) infrared non-contact thermometer	2026/05/08 00:03	communication, i2c, temperature, mlx90614, gy-906, modul, infrared, non-contact thermometer, dsp, pwm, smbus, hailege
• lamaPLC: PCF857x I/O Expander chip/modul with I ² C communication	2026/05/15 01:03	communication, i2c, pcf857x, pcf8574, pcf8574a, pcf8575, i o expander, i o extension, nxp, texas instruments
• LamaPLC: Pixart PAJ7620U2 Gesture recognition sensors/module with I ² C communication	2026/04/23 21:52	paj7620u2, gy-paj7620, pixart, gesture recognition, i2c, communication, sensor, arduino, code
• lamaPLC: RP2040_ETH_Modul: I ² C scanner	2026/05/12 16:20	code, micropython, 2026, rp2040 eth, i2c, comunication
• lamaPLC: RP2040_ETH_Modul: MLX90614 simple	2026/05/12 17:06	code, micropython, 2026, rp2040 eth, i2c, communication, mlx90614
• lamaPLC: RP2040_ETH_Modul: Read BME 680/688 sensor data	2026/05/12 21:06	code, micropython, 2026, rp2040 eth, bme680, i2c, sensor, communication
• lamaPLC: RP2040_ETH_Modul: Read BME 680/688 sensor data and store in Modbus input registers	2026/05/12 21:04	code, micropython, 2026, rp2040 eth, bme680, i2c, sensor, communication
• LamaPLC: SC16IS750 / SC16IS752: One or two serial (UART) ports from microcontroller via I ² C or SPI communication	2026/04/23 21:52	cjmcu-750, cjmcu-752, cjmcu, nxp, sc16is750, sc16is752, uart, serial, i2c, spi, modul, converter, arduino, code

- [LamaPLC: SGP Sensirion TVOC/VOC sensors with I²C communication](#) 2026/04/15 19:41 [sgp30, sgp40, sgp41, sensirion, gas-sensor, i2c, communication, sensor, arduino, code, eco2, voc, tvoc, indoor air quality, iaq, nox, hydrogen](#)
- [LamaPLC: SHT Sensirion Temperature/humidity sensor with I²C communication](#) 2026/04/23 21:52 [sht20, sht21, sht25, sht30, sht31, sht35, sht40, gy21, temperature, humidity, i2c, communication, sensor, arduino, code](#)
- [lamaPLC: Signal level converters](#) 2026/02/14 23:47 [pca9306, i2c, voltage, level, converter](#)
- [lamaPLC: st756x display drivers](#) 2026/05/20 16:17 [display, driver, i2c, spi, lcd, cog, oled, st7565, st7567, gm12864, gm12864-59n, gm12864-03a, gm12864-01a, gme12864-41](#)
- [lamaPLC: TCA9548A \(HW617\); Low-Voltage 8-Channel I²C Switch Module](#) 2026/02/14 23:51 [tca9548a, hw617, i2c, switch, communication, expansion board, arduino](#)
- [lamaPLC: TM1637 7-segment display](#) 2026/02/14 18:26 [i2c, 7-segment display, display, tm1637, arduino](#)
- [LamaPLC: TOFnnnC STMicroelectronics Time-of-Flight \(ToF\) sensors with I²C communication](#) 2026/04/23 21:52 [tof050c, vl6180, tof200c, vl53l0x, tof400c, vl53l1x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code](#)
- [LamaPLC: VL53Lnn STMicroelectronics time-of-flight \(ToF\) laser-ranging sensors with I²C communication](#) 2026/04/23 21:52 [vl53l0x, vl53l1x, vl53l0 1xv2, gy-530, time-of-flight, tof, laser-ranging, i2c, communication, sensor, arduino, code](#)
- [LamaPLC: VL6180X STMicroelectronics Time-of-Flight \(ToF\) sensor with I²C communication](#) 2026/04/23 21:52 [vl6180x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code](#)
- [lamaPLC: XGZP68xx: Silicon Pressure Sensors/Module](#) 2026/05/15 15:17 [communication, i2c, sensor, modul, pressure, cfsensor, xgzp68xx, xgzp6810d, xgzp6857d, xgzp6859d, xgzp6887d, xgzp6897d, xgzp6899a, piezoresistive, capacitive](#)
- [Magnetic angle sensors](#) 2026/04/23 21:52 [magnetic angle sensor, magnetic flux, sensor, spi, i2c, pwm, communication, modul, as5047p, as5600, mt6701, mt6816, mt6835, tle5012b, amr, gmr, tmr, anisotropic magnetoresistive](#)
- [SSH1106/SSD1306 OLED Display with I²C communication](#) 2026/02/14 18:27 [i2c, oled, display, ssd1306, sh1106, ssh1106, arduino, cmos](#)

[Avago, APDS-9900, APDS-9930, APDS-9960, ALS, proximity, detection, gesture recognition, gesture, i2c, communication, sensor, arduino, code](#)

This page has been accessed for: Today: 1, Until now: 220

From:

<https://lamaplc.com/> - **lamaPLC**

Permanent link:

<https://lamaplc.com/doku.php?id=sensor:apds>

Last update: **2026/04/21 20:47**

